

INFORMA



Speech Dialler

The Informa is a Speech Dialler for use with intruder alarm systems.

previously recorded message, thereby alerting the recipient of the call to the alarm and potential intrusion.

The Informa is a keypad unit that uses a telephone line to dial pre-programmed telephone numbers. It then replays a

Features:

- Up to three telephone numbers can be designated and memorized by the Informa.
- Unique, easy to use "Follow me" telephone number that can be programmed by the end user. The Follow me feature is designed to be used by customers who move from one location to another, or go away on holiday.
- With "Bells Only" panels such as Optima, the Informa may be used as a single-channel dialler triggered from the bell output.
- One location message of 11s and three alarm messages of three seconds each give enough time to record comprehensive messages.
- Recorded messages and telephone numbers are stored in non-volatile memory so not lost at power loss.
- The playback volume can be adjusted to four different levels.
- Three trigger inputs, programmable as active high or low, linked to phone numbers or alarm messages.
- The Informa can perform a test call, in order to check that the telephone numbers have been set up correctly.
- Supplied with telephone lead for easy installation.
- The last triggered input is logged in the memory and can be viewed.
- Can be used as a standalone unit.

INFORMA

Speech Dialler

Specifications:	
Power Supply	Provided by the host control panel
Power Supply Voltage	10 to 18V (max)
Power Supply Current	50mA quiescent (200mA maximum when operating)
Negative Input Trigger Voltage	< 1.0V
Positive Input Trigger Voltage	3.5V to 15V (max)
LED indicators	One power LED green 4 red LEDs showing respectively the state of IP1-IP3 and Inhibit inputs
Memory Type	Non-Volatile Memory (NVM)
Temperature Range (Operating)	0 to 60°C
Dialling Method	DTMF (tone)
Ringer Equivalence Number	REN = 1
Inputs	3 Trigger Inputs IP1-IP3 1 Inhibit Input to enable the use of the Follow Me function
Phone Numbers	3 phone numbers + Follow me number
Message Length	20 seconds (11s location message + 3s per alarm message)
Access codes	2 programmable (customer and engineer)
Tamper Switch Output	Front cover and back
Dimensions	W 148mm x H 115mm x D 32mm
Weight	278g

Ordering:	
8EP276A	Informa Speech Dialler

Honeywell Security & Custom Electronics

Newhouse Industrial Estate,
Motherwell, Lanarkshire,
ML1 5SB UK
Tel +44 (0)1698 738200
Fax +44 (0)1698 738300
Literature +44 (0)870 240 3387
www.honeywell.com/security/uk/intruder

Honeywell Security & Custom Electronics

Network 121,
1446 WV Purmerend
The Netherlands
Tel +31 (0) 299-410200
Fax +31 (0) 299-410201
www.honeywell.com/security/nl

HSCE-INFORMA-01-EN(0407)DS-E
April 2007
© 2007 Honeywell International Inc.

